

## iCall CC03/MAG – LB/SC handset with magnetic connector



### General description

iCall handset to use on LB or ST call stations with magnetic call cord connection. The handset has a finding LED and an integrated reassurance LED that will be activated on a call. A wall mounting docking bracket is included. The handset has 2 light switches (via dry contact output). The housing is waterproof and connected by a 3m long cable to a 8 pins magnetic connector.

### Features

- Finding LED for easy access to call button in dark environments
- Call assurance LED indication on active call
- 2 extra light switch buttons
- Wall mounting bracket
- 90° connector
- Magnetic break contact
- 3 meter cable
- Fully Supervised on LB call stations
- Using magnetic adaptor for connecting to LB and ST call stations with PS2 connection
- Ergonomic handheld design
- Large red button is easy for patients to locate and operate
- Easy to clean, IP 67
- Shockproof plastic housing

## Order information

- NWCAIN1203 iCall CC03/MAG - LB/SC Handset
- PWBXNH0101 iCall Handset convertor PS2 (magnetic)
- NWCAES0201 iCall Handset docking bracket

## Specifications

- Protection grade IP 67
- Voltage 24 VDC
- Current Max 20 mA
- Cable length 3m
- Connector type Magnetic
- Weight 166 g